



**Product Catalogue of Tutis-Fingerprint & RFID Time Attendance system with USB Data Transfer support supporting 1500 users**

**> PRODUCTS**



**Tutis Combo -Time Attendance**

Biometric based Time & Attendance System Facility of Finger print with Proximity Cards( by default) & Passwords – all rolled into one, with a flexibility to use any one or a combination for Time Attendance system along with **USB port as** for data download along with LAN port support. User capacity of 1500 supported



**> FEATURES**

- Rugged Optical Sensor
- 1-touch 1-second user recognition
- Stores 3500 templates using Grouping and 50000 transactions
- Reads Fingerprints and/or PINs
- Built in Serial and Ethernet ports (LAN)
- Built in USB Port for data transfer
- Real time 1-touch data export to 3rd party hosted and non-hosted applications
- Audio-Visual indications for acceptance and rejections of valid/invalid fingers

**> Technical Specifications**

Capacity		Verification/Identification	
Templates:	1500	Matching:	1:N up to 3500 templates
Transactions:	50000	Verification:	≤1 second
		Identification:	≤2 seconds
		Enrollment:	≤5 seconds
		FRR	≤1%
		FAR	≤0.001%
Display		Environment	
LCD:	2.75 x 1.5 inch Graphic LCD Display	Oper. Temp:	32° - 105 °F (0°-42°C)
Communication		Power	
Port:	RS 232/RS 485	Oper. Voltage:	5V DC
Port:	Ethernet 10/100	Port:	USB Port for Data Transfer
Dimensions			
Length:	8.46 inches (215mm)		
Width:	6.88 inches (175mm)		
Depth:	2.4 inches (50mm)		

## Installation Diagram




TUTIS TECHNOLOGIES LTD.

Regd. Office : C-409, Solaris 1, Opp. L&T Gate No. 6, Saki Vihar Road, Andheri (E), Mumbai - 400072. INDIA.  
Tel.: (91-22) 2857 8240/42 Fax : (91-22) 2857 8239 Email : info@tutistech.com Website : www.tutistech.com



### Technical Specifications of Tutis-Fingerprint Time Attendance System with RFID support along with USB data transfer-TTA06-ID

	<b>Size</b>	240(L)*138(W)*46(H)mm
	<b>User Capacity</b>	1500
	<b>Transaction Storage</b>	50,000
	<b>Operating System</b>	Linux
	<b>Communications</b>	RS232 ,RS485, .TCP/IP
	<b>Identification Time</b>	<=2S
	<b>FAR</b>	<=0.0001%
	<b>FRR</b>	<=1%
	<b>LED</b>	Red, Green
	<b>LCD</b>	128*64 Blue background light
	<b>Operating Temperature</b>	0-45 degree C
	<b>Operating Humidity</b>	20%-80%
	<b>Battery Backup</b>	2 Hours
	<b>Built in Proximity Reader</b>	RFID
<b>Data Transfer</b>	USB	
<b>Fingerprint Sensor</b>	Optical 500 DPI	

TUTIS TECHNOLOGIES LTD.

Regd. Office : C-409, Solaris 1, Opp. L&T Gate No. 6, Saki Vihar Road, Andheri (E), Mumbai - 400072. INDIA.  
Tel.: (91-22) 2857 8240/42 Fax : (91-22) 2857 8239 Email : info@tutistech.com Website : www.tutistech.com